

# ChekOut/Pro™

## Professional Outlet Checker with GFCI Tester & Cord



- Tests standard 120V, 3-wire and GFCI outlets and standard outlets that are wired in series with other GFCI outlets.
- Unique hand-held design is easier to use.
- Indicates correct circuit status or specific wiring errors.
- Super-safe, zero-heat LEDs.
- Rated for 125VAC / 60Hz/ 0.2W.

**Features a 40-inch cord for those hard-to-reach outlets!**



Recessed GFCI trip button prevents accidental operation.

INDICATOR	FAULT	REASON FOR FAULT
○ ○ ○	Open Hot	Hot wire not connected or outlet de-energized
○ ● ○	Open Neutral	Neutral wire not connected
● ○ ○	Open Ground	Ground wire not connected
● ○ ●	Hot/Neutral Reversed	Hot and neutral wires are interchanged
○ ● ●	Hot/Ground Reversed	Hot and ground wires are interchanged
● ● ○	<b>Correct</b>	Receptacle is wired correctly



Reliance Controls Corporation  
 2001 Young Court  
 Racine, WI 53404  
 800-634-6155  
[www.reliancecontrols.com](http://www.reliancecontrols.com)

**RELIANCE**®  
 CONTROLS

**THP102P**